



Use of Nayax devices in a Parlevel Micro Market

PAYMENT

Payment

<input type="checkbox"/> Card Enabled	<input checked="" type="checkbox"/>
<input type="checkbox"/> Cellular Enabled	<input checked="" type="checkbox"/>
<input type="checkbox"/> Choose Product Timeout(sec)	<input type="text" value="40"/> ?
<input type="checkbox"/> Default Credit	<input type="text" value="2000"/> ?
<input type="checkbox"/> EMV Price Table	<input type="text" value="@\$"/> ?
<input type="checkbox"/> Payment Flags	<input type="text" value="Prepaid Pre-Selection + Server price for Ven..."/> ?
<input type="checkbox"/> Registration Enabled	<input checked="" type="checkbox"/>
<input type="checkbox"/> Registration Timeout	<input type="text" value="25"/>
<input type="checkbox"/> Transaction Enabled	<input checked="" type="checkbox"/> ?
<input type="checkbox"/> Transaction Timeout	<input type="text" value="25"/> ?

Default credit should be high enough for large transactions. In fact, the highest transaction you're likely to see and add two zeros, so we recommend 5000, as it should be ok for large \$50, CAD 50, GBP 50, or EUR 50 transactions

MDB





MDB

<input type="checkbox"/> Disable Sending Cash Sale Notification	<input type="checkbox"/> ?
<input type="checkbox"/> Ignore Start State	<input checked="" type="checkbox"/>
<input type="checkbox"/> Ignore VMC Configuration	<input checked="" type="checkbox"/>
<input type="checkbox"/> MDB flags	<input type="text" value="02 PreSelection Enabled"/> ?
<input type="checkbox"/> MDB Rx Timeout (sec)	<input type="text" value="60"/> ?
<input type="checkbox"/> Poll IRQ Timeout (ms)	<input type="text" value="500"/>
<input type="checkbox"/> Poll Stop Event Timeout (sec)	<input type="text" value="90"/> ?
<input type="checkbox"/> Post Cash Sale Timeout	<input type="text" value="0"/> ?
<input type="checkbox"/> Reader State Error Event Timeout (MAX: 255 sec)	<input type="text" value="0"/> ?
<input type="checkbox"/> Session Complete Timeout (ms)	<input type="text" value="500"/> ?
<input type="checkbox"/> Vend Result Timeout (MAX: 65535 sec)	<input type="text" value="255"/> ?

PRESELECT. Since this is the method used. No Pre-Authorizations.

LCD

LCD


- Cash Only Message 
- LCD Message 
- LCD Status 
- Welcome Message 

Our micro market keeps the cashless device inactive until there are products in the shopping cart, so please replace the CASH ONLY message with something like: "Welcome to Your Micro Market" in order to avoid confusion.

AUDIO

Last: Remove Audio Messages since these are meant for the purchase flow of a vending machine, not Parlevel's

Language / Audio

- Audio Language 
- LCD Primary Language  
- LCD Secondary Language  
- SRV to LCD lang  

INSTALLING THE NAYAX DEVICE

Energy

The kiosk comes with an MDB power supply (24V).

Connection to the PC

Done through a converter (a COINCO one in this next picture)

Open the connections as needed and connect the Nayax device between the energy line and the converter. If there is a bill acceptor in place, make the connection between the bill acceptor and the converter. If the converter is Qibixx brand make sure to connect the MDB line to the port labeled VMC.



If you wish to place it on the right side of the kiosk, fix it from the outside in, with fasteners inserted from the inside out. Given the thickness of the acrylic shell, the fasteners should be a little longer than those provided by Nayax in its box.



The left side may also be used, inserting it from the inside out and fixing it with hexagonal nuts.

